

迪文

客户换了一张物联网卡后不能上网。

log 发现:

```
11-22 16:11:57.564 D/SubscriptionController( 626): sim_state is :READY
11-22 16:11:57.568 D/DCT ( 626): [0]onRecordsLoadedOrSubIdChanged: createAllApnList
11-22 16:11:57.568 D/DCT ( 626): [0]createAllApnList: selection=numeric = '46008'
11-22 16:11:57.575 D/DCT ( 626): [0]createAllApnList: No APN found for carrier: 46008
11-22 16:11:57.575 D/DCT ( 626): [0]createAllApnList: X mAllApnSettings=[]
11-22 16:11:57.575 D/DCT ( 626): [0]setDataProfilesAsNeeded
11-22 16:11:57.575 D/DCT ( 626): [0]setInitialApn: E mPreferredApn=null
11-22 16:11:57.575 D/DCT ( 626): [0]setInitialAttachApn: X There in no available apn
11-22 16:11:57.575 D/DCT ( 626): [0]onRecordsLoadedOrSubIdChanged: notifying data availability
11-22 16:11:57.576 D/DCT ( 626): [0]isEmergency: result=false
```

apns-conf.xml 添加

```
<apn carrier="China Mobile CMWAP" apn="CMWAP" mcc="460" mnc="02" user="wap" password="wap" serve
<apn carrier="China Mobile CMWAP" apn="CMWAP" mcc="460" mnc="07" user="wap" password="wap" serve
<apn carrier="China Unicom 3G" mcc="460" mnc="01" apn="3gnet" port="80" type="default,supl" />
<apn carrier="China Mobile IOT" mcc="460" mnc="08" apn="cmiot" type="default,supl" />
<apn carrier="China Unicom 3G" mcc="460" mnc="09" apn="3gnet" port="80" type="default,supl" />
<apn carrier="中国联通 3g 彩信 (China Unicom)" mcc="460" mnc="01" apn="3gwap" mmsc="http://mmsc.myuni
```

将其push进板子

```
C:\Users\Administrator>adb push Quectel\apns-conf.xml /system/etc/
1742 KB/s (205394 bytes in 0.115s)

C:\Users\Administrator>adb shell
```

删除 telephony.db 后重启

```
cd /data/user_de/0/com.android.providers.telephony/databases
rk3288:/data/user_de/0/com.android.providers.telephony/databases # ls
ls
HbpcdLookup.db          mmsms.db          telephony.db
HbpcdLookup.db-journal mmsms.db-journal telephony.db-journal
rk3288:/data/user_de/0/com.android.providers.telephony/databases # rm telephony.db
m telephony.db
rk3288:/data/user_de/0/com.android.providers.telephony/databases #
rk3288:/data/user_de/0/com.android.providers.telephony/databases #
rk3288:/data/user_de/0/com.android.providers.telephony/databases # su
su
rk3288:/data/user_de/0/com.android.providers.telephony/databases # sync
sync
rk3288:/data/user_de/0/com.android.providers.telephony/databases # reboot
reboot

C:\Users\Administrator>
```

问题解决